

netlife easy system; straightforward in-house project engineering; easy installation; preset functions; simple commissioning via remote control, app, DIP switch, rotary knob, etc.

CHARACTERISTICS

Regiolux Classification	netlife easy
Control signal	Switch
Number of control gear (max)	1100VA
Communication	Wired
Sensor technology	PIR - passive infrared
Installation height (min/max)	2m to 10m
Remote control	84506027100
Optional remote control	84506021200 +App
App name	B.E.G. One
System extension	easy19
Application	Corridors, Garages, Industry, Logistics centres, Secondary rooms, Office, Meeting rooms
Function	Motion detection, presence detection, Switch

MONITORING AREA

Mounting Height	3,5m	10m
Ø max. sitting[S]	9m	-
Ø max. radial[R]	-	16m
Ø max. tangential[T]	-	48m

